

SurgeX

Installation Instructions

SX1115

Mounting

The SurgeX SX1115 is designed to be installed in a 19 inch equipment rack and requires one unit (1-U) of rack space. Remove the product from its packaging and slide it into place in the rack being careful to feed the power cord into the rack first and guide it so that it does not get caught or jammed as the product is installed. Use the four screws provided with the product to secure the rack ears to the rack rails. These screws can be tightened by hand and do not require tools.

120 Volt Connections

Connect power to the unit by plugging the cord into a 120V ac receptacle.

The SX1115 has a total of 9 receptacles: six switched, two always on and a front panel courtesy outlet. Each receptacle is rated for a maximum load of 15 amps, but the total load also must not exceed 15 amps. Plug the equipment cords into the always-on and switched receptacles as needed to power the equipment.

The always-on and courtesy receptacles provide power as long as power is supplied to the SurgeX. The six switched outlets provide power only when the front panel switch is on.

Indicator Lights

The SX1115 has a red Power light and a green Self-Test light. The red Power light indicates that the power switch is turned on and power is applied to the unit. The green Self-Test light indicates that power is applied to the unit and the internal surge protection circuitry is fully functional.